


Battery Capacity Tester

✓ AC milliohmmeter checks Battery Condition in seconds
While the battery is in service

Features:

- On-line testing without disconnecting battery
- Built-in datalogger manually stores up to 999 sets and 9600 sets for continuous datalogging
- Simultaneously measures DC Voltage and AC Milliohms
- Auto power off
- Includes Windows[®] 95/98/NT/2000/ME/XP compatible software for downloading readings to a PC



| Specifications | Range | Resolution | Basic Accuracy |
|------------------------|--------------------------------------|--------------------------|----------------------|
| Resistance | 40mΩ, 400mΩ 4Ω, 40Ω | 10μΩ, 100μΩ 1mΩ, 10mΩ | ±(1% reading ± 10d) |
| Voltage | 4V, 40V | 1mV, 10mV | ±(0.1% reading ± 6d) |
| Max Input Voltage | 50VDC | | |
| Manual Datalogging | 999 sets | | |
| Continuous Datalogging | 9600 sets | | |
| Power | 6 AA batteries | | |
| Battery life | 7 hours | | |
| Dimensions | 9.75 x 4 x 1.75" (250 x 100 x 45 mm) | | |
| Weight | 17.5oz (500g) | | |

Ordering Information:

- BT100Battery Capacity Tester
 BT102120V AC Adaptor
 BT100-ALReplacement Alligator Clips for BT100
 BT100-TLReplacement Test Leads for BT100
 USB100RS-232 to USB Adaptor

